

# EF JOHNSON 51SL ES

This document will help to familiarize you of your issued P25 Trunked 800 MHz portable radio.



- F1 = Exit/Back
- Up Down Keys
- F2 Select/Menu
- F4 Scan List Select
- F3 Scan on/off
- microphone
- Speaker

On Off Volume

Channel Select

Zone Select

Emergency Button

Latch



Scan List Select

Backlight on/off

Channel Lock On/Off toggle

Press to talk



Zone "A"  
Channel 1=UCFD Dispatch= 911 Dispatch/Communication  
Channel 2= UCFD Tac-2= Tactical channel 2  
Channel 3= UCFD Tac-3= Tactical channel 3  
Channel 4= UCFD Tac-4= Tactical channel 4  
Channel 5= UCFD Tac-5= Tactical channel 5  
Channel 6= UCFD Admin=Administration Channel (not in all radios)  
Channel 7= PD-FD Comm= PD to Fire Communication  
Channel 8= GTR Fire= Goodyear Fire Brigade  
Channel 9=Utility Channel= Electric , water, public works, etc  
Channel 10=CW Fire= County Wide FIRE channel  
Channel 11=Recue/EMT= Rescue squad/Baptist EMS  
Channel 12=CW Mutual Aid= County wide mutual aid  
Channel 13=Disaster  
Channel 14=I call= State and Nation wide communications channel  
Channel 15=Fire T/A= Union City Fire talk around  
Channel 16=I Call Dir=State and Nation wide communications channel

Zone "B"  
Channel 1= Fire T/A= Union City Fire talk around  
Channel 2= I call= State and Nation wide communications channel  
Channel 3= I Call Dir= State and nation wide talk around.  
Channel 4=I Tac 1= St/Nation Tactical Channel 1  
Channel 5= I Tac 1= St/Nation Tactical Channel 1 Direct  
Channel 6= I Tac 2= St/Nation Tactical Channel 2  
Channel 7= I Tac 2= St/Nation Tactical Channel 2 Direct  
Channel 8= I Tac 3= St/Nation Tactical Channel 3  
Channel 9= I Tac 3= St/Nation Tactical Channel 3 Direct  
Channel 10= I Tac 4= St/Nation Tactical Channel 4  
Channel 11= I Tac 4= St/Nation Tactical Channel 4 Direct  
Channel 12=TEMA= TEMA monitored channel  
Channel 13=ICAL Local= Local Gov Channel  
Channel 14=ITAC Local= Tactical Local Gov Channel  
Channel 15&16=Not programmed

Zone "C"  
Channel 1= 8 call 90= State wide channel  
Channel 2= 8 Call 90 D= State wide channel Direct  
Channel 3= 8 Tac 91= State wide Tactical channel  
Channel 4= 8 Tac 91 D= State wide Tactical channel Direct  
Channel 5= 8 Tac 92= State wide Tactical channel  
Channel 6= 8 Tac 92 D= State wide Tactical channel Direct  
Channel 7= 8 Tac 93= State wide Tactical channel  
Channel 8= 8 Tac 93 D= State wide Tactical channel Direct  
Channel 9= 8 Tac 94= State wide Tactical channel  
Channel 10= 8 Tac 93 D= State wide Tactical channel Direct  
Channel 11-16=Not Programmed

For more information please refer to the EF Johnson Manual that was e-mailed to you.